

## Studio LED X2 Fresnel 60W Daylight PO



QC LD27631D

### Principales caractéristiques

Studio LED X2 Fresnel 60W Daylight PO. (Ref : QC LD27631D)

Studio LED X2 Fresnel 60W Daylight PO. Head fitted w/Fresnel lens Ø130mm, 2m length bare ended cable (no switch), built in universal power supply (100-240V, 50/60Hz), electronic dimming 16 bit, LCD graphic display, internal sensor temperature, on board dimming, RDM-DMX in/out connectors, Pole Operated stirrup (Pan & Tilt) w/ 28mm (1 $\frac{1}{8}$  ») spigot. Supplied w/4-leaf rotating barndoor Ø200mm. (Ref : QC LD27631D)

**Spécifications techniques****Valeur de la spécification**

|             |         |
|-------------|---------|
| Capteur LED | 5 600 K |
|-------------|---------|

|           |     |
|-----------|-----|
| Puissance | 60W |
|-----------|-----|

|                           |       |
|---------------------------|-------|
| Diamètre lentille Fresnel | 130mm |
|---------------------------|-------|

|     |    |
|-----|----|
| IRC | 90 |
|-----|----|

|           |    |
|-----------|----|
| Indice IP | 54 |
|-----------|----|

|                  |        |
|------------------|--------|
| Poids projecteur | 4.7 kg |
|------------------|--------|

|                  |         |
|------------------|---------|
| Poids Controleur | 3.48 kg |
|------------------|---------|

